Integrated T8 Battery Backup

2-ft, 4-ft

Test button & indicators

Features

- Integrated T8 fixture with backup battery
- Built-in lithium batteries
- Test button and battery charging status indicator
- Easy to install and cost-effective
- 5-year warranty

Product Compliance & Certifications:

- ETL

Specifications

Color	4000K, 5000K
Wattage	9W, 18W
Length	2ft, 4ft
CRI	>80
Input Voltage	AC100-277V
Light Output	2ft: 1080lm, 4ft:2160lm
LED Type	SMD2835
Power Factor	>0.92
Luminous Efficiency	>120lm/W
Battery Backup Time	90 minutes
Beam Angle	120°
Light Output When on Battery	3W, 427.9lm
Warranty	5-year

Description

The Integrated T8 Battery Backup fixture (BB T8N) comes with an integrated battery. It can be used as a regular T8 fixture. During power outage, the battery will provide backup power for the fixture for more than 90 minutes. It has a test button for checking the light output on battery, as well as another indicator showing the battery charging status. It has over-charging and over-discharging protection for ensuring 800 battery recharging cycles. This integrated T8 battery backup fixture is a cost-effective option for providing battery powered lighting during a power outage. It is suitable for many facilities such as office buildings, schools, hotels, multifamily apartments, hallways, corridors, and stairs. It required to operate on an always-on circuit in order to keep the battery charged at all time.

Ordering Information

Product Model #	Wattage	Color	length
YSH-T806-Y01-09(integrated)4000K	9W	4000K	2ft
YSH-T806-Y01-09(integrated)5000K	9W	5000K	2ft
YSH-T812-Y01-18(integrated)4000K	18W	4000K	4ft
YSH-T812-Y01-18(integrated)5000K	18W	5000K	4ft

aleddra

425.430.4555 | info@aleddra.com | sales@aleddra.com | www.aleddra.com