

## EasiFit LED Lowbay Lamp — 60W, 90W



Aleddra EasiFit LED Lowbay Lamp is the most cost-effective retrofit option for replacing lights with E39/E40 base (also known as the mogul base) metal halide. Unlike other LED highbay/lowbay solutions which require complete replacement of the existing fixtures, Aleddra's lowbay lamp can be screwed in directly

into the existing E39/E40 socket, and the retrofit involves only the bypassing of the MH ballast. It not only saves on installation time and costs, but also removes the problem of having to dispose of old fixtures.



Aleddra EasiFit lowbay lamps come with two different lenses: clear or frosted. Both models are cULus certified. Frosted lens is used for a lower ceiling height, and the clear lens is more commonly used for higher

ceilings.

90W EasiFit LED lowbay lamp can be used as a replacement for a 250W metal halide lamp, while 60W replaces a 150W MH.

The EasiFit lowbay lamps use LG LED chips and come with a 40,000 hour, or 2-year warranty.

The lamp has an efficacy of 90 lm/w (with clear lens) and offers a CRI=82. Two different drivers are available depending on the voltage: 110V and 277V.



### Key Features

- Easy retrofit (bypassing MH ballast)
- E39/E40 base (Mogul base)
- LED chips: LG
- Efficacy: 90 lm/w (with clear lens)
- CRI 82
- Color temperature: 3000-6000K
- Input voltage: 120V and 277V (50-60Hz)
- Power factor: 0.9
- Operating temperature: -4°F to 122°F
- Rated life: 40,000 hours
- Warranty: 2 years
- cULus certified

### Ordering Information

Product Label	Watts	To replace	Lumen	Approval
AHB-XTHBB-60	60W	120-150W MH	4800 - 5400	cULus
AHB-XTHBB-90	90W	200-250W MH	7200 - 8100	cULus

#### Ordering Information:

	Wattage	Input Voltage	Base	Lens	LED Color
AHB - XTHBB -	60 - 60W	120 - 120V	40 - E40	C - Clear	30 - 3000K ± 250K
	90 - 90W	277 - 277V	39 - E39	F - Frosted	40 - 4000K ± 250K
					50 - 5000K ± 250K
					60 - 6000K ± 250K

