

## EasiFit® Troffer Kit 2x4, 2x2



### Description

Aleddra's EasiFit® Troffer Retrofit Kit is an energy-efficient cost-effective replacement for an existing linear troffer luminaire. It fits into the existing troffer housing, thus saving the labor of removing it and the trouble of disposing it. At the same time, it provides a more aesthetic appearance than the old fixture. The 0-10V dimming makes it controllable by daylighting harvest system for further energy saving. The patented design of this kit makes it very easy for installation, without using any screw.

The EasiFit Troffer Kit is UL/DLC certified for utility rebate. The fixture comes with a 7-year warranty. The 10-year warranty is optional at an incremental price.

### Key Features

- Efficacy: 126 LMW
- CCT: 3000K (for 50W), 3500K, 4000K, 5000K
- CRI > 80
- Power Factor >0.90
- Dimming: 0-10V dimmable
- Input voltage: 110V-277V
- Operating temperature: -20°F to 122°F
- Size:
  - 2x2: 22.52"L x 20.67"W x 2.6"H
  - 2x4: 46.61"L x 20.67"W x 2.6"H
- Weight: 2x2 at 5.3lbs, 2x4 at 10.8 lbs
- Certification: **UL, DLC**
- Warranty: 7 years (10-year optional)
- **Easy installation: no screw needed**

### Ordering Information

| Product Label     | Size | Wattage | Lumen | Color |
|-------------------|------|---------|-------|-------|
| AT-R4-25W-XDZ-35K | 2x2  | 25W     | 3300  | 3500K |
| AT-R4-25W-XDZ-40K | 2x2  | 25W     | 3300  | 4000K |
| AT-R4-25W-XDZ-50K | 2x2  | 25W     | 3300  | 5000K |
| AT-R4-36W-XDZ-35K | 2x2  | 36W     | 5000  | 3500K |
| AT-R4-36W-XDZ-40K | 2x2  | 36W     | 5000  | 4000K |
| AT-R4-36W-XDZ-50K | 2x2  | 36W     | 5000  | 5000K |
| AT-R7-36W-XDZ-35K | 2x4  | 36W     | 4900  | 3500K |
| AT-R7-36W-XDZ-40K | 2x4  | 36W     | 4900  | 4000K |
| AT-R7-36W-XDZ-50K | 2x4  | 36W     | 4900  | 5000K |
| AT-R7-50W-XDZ-30K | 2x4  | 50W     | 6200  | 3000K |
| AT-R7-50W-XDZ-35K | 2x4  | 50W     | 6300  | 3500K |
| AT-R7-50W-XDZ-40K | 2x4  | 50W     | 6300  | 4000K |
| AT-R7-50W-XDZ-50K | 2x4  | 50W     | 6300  | 5000K |